

LD-ATD-GSM-V1.0

GSM AUTO DIALLER



OVERVIEW

Auto Dialler widely using in security devices to activate the voice call at the time of risk.

Trigger input from Main Alarm will activate the Dial mode of Auto dialler and dial to programmed phone numbers. At the other end receiver gets call and pre-recorded voice message. LDX introduces Version1.0 GSM auto dialler which enhanced with quad-band GSM module along with high sensitive and powerful coding.



Technical specification

Operating voltage	12vDC
GSM Module	Quad-band
Total phone number	15
Voice memory	30secMax
Triggering Voltage	8-12v
Display	16*2line LCD
Input method	4*3 keypad
Initializing Time	20-60sec
Dimension	18cm*13cm*5.5cm

LD-ATD-GSM-V1.0

GSM AUTO DIALLER



Features

- ▶ Quad band GSM module can support all networks.
- ▶ Can be added up to 15 call voice alert receivers even land line and mobile numbers
- ▶ Very easy commands to program the phone numbers and voice recording.
- ▶ Pass word production,without prompt password cannot be reprogram.
- ▶ LCD display makes program easy.
- ▶ Clear voice output.
- ▶ External Antenna(optional).
- ▶ Powder coated sheet metal cabinet.
- ▶ Any external input like Door switch, PIR and Vibration switch can be connected.

Operating Commands

Default password is 1111

*01--015# to enter 1-15 phone numbers to be added as alert receivers.

*88# to record voice , after pressing this command Record ready LED will be ON. when finished recording press# to stop recording.

*99# to play the recorded voice through external speaker, after listen press# to stop play.

*66# to delete entire phone numbers.

*77# to dial entire phone numbers manually.

*55# to change current password.

press# after every command to finish.

Why LDX

LDX automation's motto is 'simplify the intelligence'. It is enforcing continual focus on converting ideology into simplified and easy understanding materializations. All LDX products are designed toward reducing attempts to study the product operation. LDX ensures the products with quality and on site customer feel.